

A wavelet-Galerkin algorithm of the E/B decomposition of CMB polarization maps

Liang Cao^{1,2} and Li-Zhi Fang³

ABSTRACT

We develop an algorithm of separating the E and B modes of the CMB polarization from the noisy and discretized maps of Stokes parameter Q and U in a finite area. A key step of the algorithm is to take a wavelet-Galerkin discretization of the differential relation between the E , B and Q , U fields. This discretization allows derivative operator to be represented by a matrix, which is exactly diagonal in scale space, and narrowly banded in spatial space. We show that the effect of boundary can be eliminated by dropping a few DWT modes located on or nearby the boundary. This method reveals that the derivative operators will cause large errors in the E and B power spectra on small scales if the Q and U maps contain Gaussian noise. It also reveals that if the Q and U maps are random, these fields lead to the mixing of the E and B modes. Consequently, the B mode will be contaminated if the powers of E modes are much larger than that of B modes. Nevertheless, numerical tests show that the power spectra of both E and B on scales larger than the finest scale by a factor of 4 and higher can reasonably be recovered, even when the power ratio of E - to B -modes is as large as about 10^2 , and the signal-to-noise ratio is equal to 10 and higher. This is because the Galerkin discretization is free of false correlations, and keeps the contamination under control. As wavelet variables contain information of both spatial and scale spaces, the developed method is also effective to recover the spatial structures of the E and B mode fields.

Subject headings: cosmology: theory - cosmic microwave background

¹Key Laboratory for Research in Galaxies and Cosmology, Shanghai Astronomical Observatory, Chinese Academy of Sciences, 80 Nandan Road, Shanghai 200030, China

²Graduate University of the Chinese Academy of Science, 19A Yuquan Road, Beijing 100049, China

³Department of Physics, University of Arizona, Tucson, AZ 85721

1. Introduction

The scalar component of primordial perturbations of the universe can be detected by the maps of temperature fluctuations of Cosmic Microwave Background Radiation (CMBR), while the tensor component of the primordial perturbations has to be probed by the maps of the Stokes parameter Q and U of the linear polarization of the CMBR. A tensor field generally contains electric-like E -mode and magnetic-like B -modes. In the linear regime, vortical mode of primordial perturbations do not grow during the clustering of density field, and therefore, the perturbed field initially has to be curl-free. That is, the primordial perturbations can only yield the E -mode, but not B -mode of the CMBR polarization field. On the other hand, B -mode perturbations can be produced by gravitational waves. Therefore, extracting the B -mode information from CMBR polarization maps is crucial to verify the existence of gravitational wave background produced at the inflationary epoch. Moreover, gravitational lensing of clusters and hot electron scattering of reionization would be able to yield both E - and B -modes. To study these problems a sharp decomposition of E - and B -modes from Q and U maps is required.

If both Q and U maps are available over the whole sky, one can find the whole sky maps of E - and B -modes with the spherical harmonic decomposition, because the relation between the maps of (Q, U) and (E, B) in the space spanned by bases of spin two harmonics is local (Kamionkowski et al. 1997; Zaldarriaga & Seljak 1997). However, the observed maps cannot be global; it is always limited by the contamination of our galaxy and other foreground sources. The relation between the maps of (Q, U) and (E, B) in physical space contains the Laplace operator, and therefore, it is non-local. The E/B decomposition with the spatially-limited maps of Q and U will not be unique if we lack of information of the polarization and its derivative on the boundary of the maps.

For noiseless samples, the problem of uniqueness would be solved by constructing orthogonal modes with window functions to fit the requirements of boundary conditions (Lewis et al. 2002; Bunn et al. 2003; Smith 2006; Smith & Zaldarriaga 2007). It is, however, similar to the domain (or windowed) Fourier analysis. The result will not be useful to study the structures in physical space (e.g. Chiueh & Ma 2002).

The other challenge caused by the derivative operator is because the Q and U maps are discrete. Mathematically, the derivative operators ∂_x or ∂_x^2 are continuous linear operators mapping functions defined in Hilbert space, while the observed samples Q and U actually are defined in space spanned by base v_i , $i \in I$, which is a set of finite indices. This difference leads to large numerical errors when the discrete maps are noisy.

The last, but not least, problem is from the smallness of B -modes. On the scale of one

degree order, the power of B -mode caused by gravitational waves at inflationary epoch is less than that of E -modes by a factor of at least 10^2 . As the maps of Q and U are random fields, the variance of the random fields will lead to the mixing of E - and B -modes. Consequently, E - and B -modes would be contaminated from each other. Therefore, it is difficult to recover the power of B -mode if the powers of E modes are much larger than that of B modes.

In this paper, we develop an algorithm of the E/B decomposition based on the discrete wavelet transform (DWT) analysis, which is a compromise between the decompositions in physical space and scale space. The DWT analysis of the CMBR temperature fluctuation maps has attracted much attention in the last decade (Pando et al. 1998; Sanz et al. 1999; Mukherjee et al. 2000). Besides these points, we especially take the advantage of the so-called wavelet-Galerkin discretization (e.g. Louis et al. 1997), which is to approximate derivative operator to a matrix in space spanned by wavelet bases. For some available wavelets, the matrixes are exactly diagonal in scale-space, and narrowly banded in spatial space. This made the uncertainties from boundary, noises and variances are under control. We will study the conditions, under which the information of small B -mode can approximately be extracted from noisy maps of Q and U .

The paper is organized as follows. Section 2 presents the method of the E/B separation in the DWT space. Section 3 tests the DWT algorithm with samples with known spatial structures. We show that the method effectively to suppresses the uncertainties from boundary effect and noise. It is also effective to identify spatial structures of E and B fields. Section 4 presents the tests for samples of Gaussian random field. The effect of the variance of Gaussian random field is analyzed, especially the problem of the mixing of E - and B -modes. Section 5 addresses the effectiveness of the wavelet-Galerkin discretization. Finally conclusions are given in Section 6. The DWT representation of derivative operators are given in the Appendix.

2. Method

2.1. E/B separation in DWT representation

Let us consider polarization samples in a patch of sky, which can be approximated as a plane described by Cartesian coordinates (x, y) . In this case, the fields of $E(x, y)$ and $B(x, y)$ are related to the maps of Stokes parameters $Q(x, y)$ and $U(x, y)$ by (Seljak 1997)

$$\nabla^2 E(x, y) = (\partial_x^2 - \partial_y^2)Q(x, y) + 2\partial_x\partial_y U(x, y) \quad (1)$$

$$\nabla^2 B(x, y) = 2\partial_x\partial_y Q(x, y) - (\partial_x^2 - \partial_y^2)U(x, y) \quad (2)$$

where ∇^2 is 2-D Laplace $\partial_x^2 + \partial_y^2$.

We first take a wavelet-Galerkin discretization of equations (1) and (2) to rewrite these equations in the DWT space. We can assume that the patch is a $L \times L$ square. The size of each pixel is $L/2^J$, J being a integral, one can project the maps into the DWT space by

$$\epsilon_{l_1, l_2}^Q = \int Q(x, y) \phi_{J, l_1}(x) \phi_{J, l_2}(y) dx dy \quad (3)$$

$$\epsilon_{l_1, l_2}^U = \int U(x, y) \phi_{J, l_1}(x) \phi_{J, l_2}(y) dx dy \quad (4)$$

where $\phi_{J, l}(x)$ is orthogonal scaling function on scale J (e.g. Fang & Thews 1998). It is non-zero mainly in the cell in x -space from $lL/2^J$ to $(l+1)L/2^J$. The index l runs from 0 to $2^J - 1$. It spans the spatial range from 0 to L . The variables ϵ_{l_1, l_2}^Q and ϵ_{l_1, l_2}^U actually are the maps of Q and U on scale J . Since the observed maps of Q and U are always pixelized, the projection of eqs.(3) and (4) does not lose information if the size $L/2^J$ is the same as that of pixels of observed samples.

One can further take a projection on eqs.(1) and (2) as

$$\langle \nabla^2 E(x, y), \phi_{J, l_1}(x) \phi_{J, l_2}(y) \rangle = \langle (\partial_x^2 - \partial_y^2) Q(x, y) + 2\partial_x \partial_y U(x, y), \phi_{J, l_1}(x) \phi_{J, l_2}(y) \rangle \quad (5)$$

$$\langle \nabla^2 B(x, y), \phi_{J, l_1}(x) \phi_{J, l_2}(y) \rangle = \langle 2\partial_x \partial_y Q(x, y) - (\partial_x^2 - \partial_y^2) U(x, y), \phi_{J, l_1}(x) \phi_{J, l_2}(y) \rangle. \quad (6)$$

With the DWT decomposition of $E(x, y)$ and $B(x, y)$

$$E(x, y) = \sum_{l_1, l_2} \epsilon_{l_1, l_2}^E \phi_{J, l_1}(x) \phi_{J, l_2}(y), \quad \epsilon_{l_1, l_2}^E = \int E(x, y) \phi_{J, l_1}(x) \phi_{J, l_2}(y) dx dy \quad (7)$$

$$B(x, y) = \sum_{l_1, l_2} \epsilon_{l_1, l_2}^B \phi_{J, l_1}(x) \phi_{J, l_2}(y), \quad \epsilon_{l_1, l_2}^B = \int B(x, y) \phi_{J, l_1}(x) \phi_{J, l_2}(y) dx dy \quad (8)$$

eqs.(5) and (6) yield matrix equations

$$\sum_{l'_1, l'_2} [T_{l_1, l'_1}^{(2)} \delta_{l_2, l'_2} + T_{l_2, l'_2}^{(2)} \delta_{l_1, l'_1}] \epsilon_{l'_1, l'_2}^E = \sum_{l'_1, l'_2} \{ [T_{l_1, l'_1}^{(2)} \delta_{l_2, l'_2} - T_{l_2, l'_2}^{(2)} \delta_{l_1, l'_1}] \epsilon_{l'_1, l'_2}^Q + 2T_{l_1, l'_1}^{(1)} T_{l_2, l'_2}^{(1)} \epsilon_{l'_1, l'_2}^U \} \quad (9)$$

$$\sum_{l'_1, l'_2} [T_{l_1, l'_1}^{(2)} \delta_{l_2, l'_2} + T_{l_2, l'_2}^{(2)} \delta_{l_1, l'_1}] \epsilon_{l'_1, l'_2}^B = \sum_{l'_1, l'_2} \{ 2T_{l_1, l'_1}^{(1)} T_{l_2, l'_2}^{(1)} \epsilon_{l'_1, l'_2}^Q - [T_{l_1, l'_1}^{(2)} \delta_{l_2, l'_2} - T_{l_2, l'_2}^{(2)} \delta_{l_1, l'_1}] \epsilon_{l'_1, l'_2}^U \} \quad (10)$$

where the matrix $T_{l, l'}^{(n)}$ is given by

$$T_{l, l'}^{(n)} = \int \phi_{J, l}(x) \partial_x^n \phi_{J, l'}(x) dx. \quad (11)$$

Obviously we can do the projection of eqs.(5) and (6) using any bases in 2-D space $L \times L$. However, for proper wavelet scaling functions, the integral $\int \phi_{J,l}(x) \partial_x^n \phi_{J',l'}(x) dx$ are zero for $J \neq J'$. This point is important for a wavelet-Galerkin discretization (see discussion in §4). In this case, all quantities of eqs.(9) and (10) are on scale J , and eq.(11) gives

$$T_{l,l'}^{(n)} = \frac{1}{h^n} r_{l-l'}^{(n)} \quad (12)$$

where $h = 1/2^J$. $r_{l-l'}^{(n)}$ is non-zero only in a narrow band $|l - l'| < M$, where M is an integral, depending on wavelet. For Daubechies 6 wavelet, the non-zero coefficients $r_{l-l'}^{(n)}$ are $|l - l'| \leq 4$, or $M = 4$. The values of $r_{l-l'}^1$ and $r_{l-l'}^2$ of Daubechies 6 wavelet are listed in Table 1 of Appendix.

Thus, eqs.(1) and (2) defined in continuous space (x, y) are reduced to eqs.(9) and (10) defined in a space spanned by orthogonal bases $\phi_{J,l_1}(x) \phi_{J,l_2}(y)$. The discretized Eqs.(9) and (10) are an approximation of eqs.(1) and (2). Equations(9) and (10) do not contain information on scales less than $L/2^J$. However, this discretization is reasonable in the sense that it does not introduce false correlations, or lose information of discrete datasets Q and U . The derivative operator on a function defined in a space spanned by bases $\phi_{J,l_1}(x) \phi_{J,l_2}(y)$ will yield a function in the same space. This is required by a wavelet-Galerkin discretization (§4). It ensures no signal to be produced on scales less than $L/2^J$. The eqs.(9) and (10) give a E/B decomposition from observed maps Q and U .

It should be pointed out that not all wavelets yield J -diagonal matrices like eq.(12). For instance, the popular wavelet Daubechies 4 is not suitable for this discretization, as the matrix of derivative operator in space spanned by Daubechies 4 scaling functions is not J -diagonal. More discussion on the wavelet-Galerkin discretization will be given in §4. We will first study how to develop the algorithm of the E/B decomposition with eqs.(9) and (10).

2.2. Maps of $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$

Equations(9) and (10) can be rewritten as follows

$$\sum_{l'_1, l'_2} \mathbb{M}_{(l_1, l_2); (l'_1, l'_2)} \epsilon_{l'_1, l'_2}^E = \mathbb{E}_{l_1, l_2}, \quad (13)$$

$$\sum_{l'_1, l'_2} \mathbb{M}_{(l_1, l_2); (l'_1, l'_2)} \epsilon_{l'_1, l'_2}^B = \mathbb{B}_{l_1, l_2}, \quad (14)$$

where the matrix $\mathbb{M}$ is

$$\mathbb{M}_{(l_1, l_2); (l'_1, l'_2)} = T_{l_1, l'_1}^{(2)} \delta_{l_2, l'_2} + T_{l_2, l'_2}^{(2)} \delta_{l_1, l'_1}. \quad (15)$$

If we use Daubechies 6, $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ are given by

$$\mathbb{E}_{l_1, l_2} = \sum_{m_1=-4}^4 T_{m_1}^{(2)} \epsilon_{l_1+m_1, l_2}^Q - \sum_{m_2=-4}^4 T_{m_2}^{(2)} \epsilon_{l_1, l_2+m_2}^Q + \sum_{m_1, m_2=-4}^4 2T_{m_1}^{(1)} T_{m_2}^{(1)} \epsilon_{l_1+m_1, l_2+m_2}^U, \quad (16)$$

$$\mathbb{B}_{l_1, l_2} = \sum_{m_1, m_2=-4}^4 2T_{m_1}^{(1)} T_{m_2}^{(1)} \epsilon_{l_1+m_1, l_2+m_2}^Q - \sum_{m_1=-4}^4 T_{m_1}^{(2)} \epsilon_{l_1+m_1, l_2}^U + \sum_{m_2=-4}^4 T_{m_2}^{(2)} \epsilon_{l_1, l_2+m_2}^U. \quad (17)$$

The equations (13) and (14) look like the matrix equations of the DWT variables of E and B fields, ϵ_{l_1, l_2}^E and ϵ_{l_1, l_2}^B . Equations(16) and (17) give, the sources $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ on the right hand side of eqs.(13) and (14), respectively. It seems that one can separate E/B by solving the matrix eqs.(13) and (14). However, with the coefficients $T_{l, l'}^{(n)}$ given in Appendix, we can show

$$\sum_{l'_1, l'_2} \mathbb{M}_{(l_1, l_2); (l'_1, l'_2)} = 0. \quad (18)$$

That is, the matrix $\mathbb{M}$ is singular. One cannot use a standard linear solver to solve eqs.(13) and (14). This problem, of course, is directly related to the non-uniqueness of the solutions $E(x, y)$ and $B(x, y)$ given by the Poisson equations (1) and (2) without knowledge of boundary conditions. We will not try to solve the singular matrix equations (13) and (14), but directly use eqs.(16) and (17) for the E/B decomposition.

2.3. E/B decomposition with $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$

The spatial resolution of the source terms $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ is the same as maps Q and U . It can be used to calculate the DWT power spectrum of $\nabla^2 E$ and $\nabla^2 B$ fields, and other statistics. To do these, we should first find the wavelet function coefficient (WFC) of the maps $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ by

$$\hat{\epsilon}_{\mathbf{j}, \mathbf{l}}^{\mathbb{E}} = \sum_{\mathbf{l}'} C_{\mathbf{j}, \mathbf{l}, \mathbf{l}'} \mathbb{E}_{\mathbf{l}'} \quad (19)$$

$$\hat{\epsilon}_{\mathbf{j}, \mathbf{l}}^{\mathbb{B}} = \sum_{\mathbf{l}'} C_{\mathbf{j}, \mathbf{l}, \mathbf{l}'} \mathbb{B}_{\mathbf{l}'} \quad (20)$$

where, for simplification, we use 2-D vector notation defined by $\mathbf{j} = (j_1, j_2)$ and $\mathbf{l} = (l_1, l_2)$, and $l_1 = 0 \dots 2^{j_1} - 1$, $l_2 = 0 \dots 2^{j_2} - 1$; j_1, j_2 can be any integral less than J . Index $(\mathbf{j}, \mathbf{l})$ refers to the cell on scale $\mathbf{j}$ and at position $\mathbf{l}$. The $\mathbf{l} \times \mathbf{l}'$ matrix $C_{\mathbf{j}, \mathbf{l}, \mathbf{l}'}$ is given by

$$C_{\mathbf{j}; (\mathbf{l}, \mathbf{l}')} = \int \psi_{j_1, l_1}(x) \psi_{j_2, l_2}(y) \phi_{J, l'_1}(x) \phi_{J, l'_2}(y) dx dy \quad (21)$$

where $\psi_{j,l}(x)$ is 1-D wavelet function referring to cell on scale j and at position l . $C_{\mathbf{j},(\mathbf{l},l')}$ is a banded matrix with respect to $\mathbf{l}, l'$. Therefore, the relation between $\tilde{\epsilon}_{\mathbf{j},\mathbf{l}}^{\mathbb{E}}$, $\tilde{\epsilon}_{\mathbf{j},\mathbf{l}}^{\mathbb{B}}$ and Q , U are spatially quasi-local.

With the WFCs, the DWT power spectrum is given by (Fang & Feng 2000)

$$P_{\mathbf{j}}^{\mathbb{E},\mathbb{B}} = \langle (\tilde{\epsilon}_{\mathbf{j},\mathbf{l}}^{\mathbb{E},\mathbb{B}})^2 \rangle \quad (22)$$

where $\langle \dots \rangle$ is the average over all cells $\mathbf{l}$. One can directly use the DWT power spectrum to measure E - and B -modes. $P_{\mathbf{j}}^{\mathbb{E},\mathbb{B}}$ is banded Fourier power spectrum. For a statistically homogeneous random field, the DWT power spectrum is related to the Fourier power spectrum $P^{\mathbb{E},\mathbb{B}}(n_1, n_2)$ of $(\mathbb{E}, \mathbb{B})$ maps by

$$P_{\mathbf{j}}^{\mathbb{E},\mathbb{B}} = \frac{1}{L^2} \sum_{n_1, n_2 = -\infty}^{\infty} |\hat{\psi}(n_1/2^{j_1}) \hat{\psi}(n_2/2^{j_2})|^2 P^{\mathbb{E},\mathbb{B}}(n_1, n_2). \quad (23)$$

Clearly, $P_{\mathbf{j}}$ is banded Fourier power spectrum with the window function

$$W_{\mathbf{j}}(n_1, n_2) = \frac{1}{L^2} |\hat{\psi}(n_1/2^{j_1}) \hat{\psi}(n_2/2^{j_2})|^2. \quad (24)$$

Function $\hat{\psi}(n)$ is the Fourier transform of the basic wavelet. $P_{\mathbf{j}}$ contain all valuable quantities of second order statistics from random samples in a finite area $L \times L$ and pixel $L/2^J$. The window function may cause spurious features and false correlation, such as aliasing effect, in the Fourier power spectrum. With the DWT analysis, the aliasing effects can be effectively suppressed (Fang & Feng 2000).

2.4. Effect of noise on power spectrum

The maps of Q and U are usually noisy and can be given by $Q + \Delta Q$, and $U + \Delta U$. The DWT variables of noisy DWT maps are then $\epsilon_{\mathbf{l}}^Q + \Delta Q_{\mathbf{l}}$ and $\epsilon_{\mathbf{l}}^U + \Delta U_{\mathbf{l}}$, where $\Delta Q_{\mathbf{l}}$ and $\Delta U_{\mathbf{l}}$ are the DWT variables of ΔQ and ΔU . Assuming the noise is Gaussian and statistically homogeneous, the DWT variables $\Delta Q_{\mathbf{l}}$ and $\Delta U_{\mathbf{l}}$ of noise have to satisfy the following statistical properties

$$\langle \Delta Q_{\mathbf{l}} \Delta Q_{\mathbf{l}'} \rangle = \sigma_Q^2 \delta_{\mathbf{l},\mathbf{l}'}, \quad \langle \Delta U_{\mathbf{l}} \Delta U_{\mathbf{l}'} \rangle = \sigma_U^2 \delta_{\mathbf{l},\mathbf{l}'}, \quad \langle \Delta Q_{\mathbf{l}} \Delta U_{\mathbf{l}'} \rangle = 0 \quad (25)$$

where σ_Q and σ_U are the variance of the noise of Q and U maps, respectively, and are independent of l .

Using ΔQ_1 and ΔU_1 to replace ϵ_1^Q and ϵ_1^U in eqs.(16) and (17), we can construct the noise maps of $\Delta \mathbb{E}_1$ and $\Delta \mathbb{B}_1$. First, with eq.(25) we can show

$$\langle \Delta \mathbb{E}_1 \Delta \mathbb{B}_1 \rangle = 0. \quad (26)$$

That is, noise eq.(25) does not cause false correlation between E and B modes. This is very helpful for the E/B decomposition. Second, with eqs.(16) and (17), one can find the variance of the noise maps $\Delta \mathbb{E}_1$ and $\Delta \mathbb{B}_1$ to be

$$\langle (\Delta \mathbb{E}_1)^2 \rangle = N^{(1)} \sigma_U^2 + N^{(2)} \sigma_Q^2 \quad (27)$$

$$\langle (\Delta \mathbb{B}_1)^2 \rangle = N^{(1)} \sigma_Q^2 + N^{(2)} \sigma_U^2 \quad (28)$$

where

$$N^{(1)} = \left[2 \sum_{m=1}^4 (T_m^{(1)})^2 \right]^2, \quad N^{(2)} = 2 \sum_{m=1}^4 [T_m^{(2)}]^2. \quad (29)$$

$N^{(1)}$ and $N^{(2)}$ are from the terms containing $T_{l-l'}^{(1)}$ and $T_{l-l'}^{(2)}$, respectively, in eqs.(16) and (17). For Daubechies 6 wavelet, $\sqrt{N^{(1)}} \simeq 1.2$ and $\sqrt{N^{(2)}} \simeq 5$. That is, in the Daubechies 6 DWT algorithm [eqs(16) and (17)], the operator of derivative ∂ does not significantly change the level of the noise, while the operator for ∂^2 leads to an increase of the variance by a factor of 5 with respect to the variance of ΔQ and ΔU maps. This shows that derivative will generally amplify the effect of noise. However, the matrix $T_{l,l'}^{(n)}$ is exactly diagonal with respect to j , the derivative operator in the DWT representation does not transfer the noise from one scale to others. In this sense, we have a handle on the noise.

As noise and signal are statistically uncorrelated, the power spectrum of $\mathbb{E}_1$ and $\mathbb{B}_1$ can be reconstructed by subtracting the power of noise as

$$P_j^E = P_j^{\mathbb{E}} - P_j^{\Delta \mathbb{E}} \quad (30)$$

$$P_j^B = P_j^{\mathbb{B}} - P_j^{\Delta \mathbb{B}} \quad (31)$$

where $P_j^{\mathbb{E}}$ and $P_j^{\mathbb{B}}$ are the DWT power spectrum of maps $\mathbb{E}_1$ and $\mathbb{B}_1$ given by eqs.(16) and (17), respectively, using noisy Q and U . $P_j^{\Delta \mathbb{E}}$ and $P_j^{\Delta \mathbb{B}}$ are the DWT power spectra of noise maps $\Delta \mathbb{E}_1$ and $\Delta \mathbb{B}_1$. The algorithm of subtracting the noise DWT power spectrum $P_j^{\Delta \mathbb{E}}$ and $P_j^{\Delta \mathbb{B}}$ scale-by-scale is similar to the subtraction of shot noise power from the DWT power spectrum of galaxy survey (Fang & Feng 2000).

2.5. The effect of boundary

For a sample of finite area, the DWT power spectrum analysis does not need a window function to treat the spatial domain. The effect of boundary can effectively be reduced by

dropping the DWT variables related to cells (j, l) located on or near the boundary (Pando & Fang 1998). When derivative operators, ∂_x, ∂_y , are involved, the boundary effect would be more serious, because the matrix of derivative operators in the DWT representation is not exactly diagonal with respect to the spatial index l . Nevertheless, the matrix $T_{l,l'}^{(n)}$ [eq.(11)] is narrowly banded, the effect of boundary can still be reduced by dropping boundary modes.

3. Tests with samples having known spatial structures

To test the DWT algorithm developed in §3, we consider, in this section, samples with given spatial structures, and compare the maps $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$ given by eqs.(16) and (17) with that directly calculated from E and B . This comparison is only to test the discretization of derivative operator, but says nothing about the amount of information loss associated with the algorithm.

3.1. Samples

We use two scalar functions $\psi_E(x, y)$ and $\psi_B(x, y)$ to produce E and B maps in 2-D space by the following way

$$E = -\nabla^2 \psi_E, \quad B = -\nabla^2 \psi_B. \quad (32)$$

One can then produce the DWT variables $\epsilon_{l,l'}^E$ and $\epsilon_{l,l'}^B$ with eqs.(7) and (8). With these results, we can further produce the maps of $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$ with eqs.(13) and (14). Thus, for given scalar functions $\psi_E(x, y)$ and $\psi_B(x, y)$, we have the samples $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$, and then, the the DWT power spectrum and other statistical properties of maps $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$. The ratio between the powers of E - and B -modes can be adjusted by the ratio between the functions ψ_E and ψ_B .

On the other hand, using the function $\psi_E(x, y)$ and $\psi_B(x, y)$, one can produce the samples of the Stokes parameters $Q(x, y)$ and $U(x, y)$ maps by

$$Q(x, y) = (\partial_x \partial_x - \partial_y \partial_y) \psi_E(x, y) - 2 \partial_x \partial_y \psi_B(x, y), \quad (33)$$

$$U(x, y) = 2 \partial_x \partial_y \psi_E(x, y) + (\partial_x \partial_x - \partial_y \partial_y) \psi_B(x, y). \quad (34)$$

We add Gaussian white noise in the Q and U maps pixel-by-pixel with signal-to-noise ratio equal to 10, 50, and 100. These Q and U maps are used as the simulation of observed samples.

With noisy maps Q and U , we can produce the variables $\epsilon_{l,l'}^Q$ and $\epsilon_{l,l'}^U$ by the projection of eqs.(3) and (4). Finally, we have maps $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$ using eqs.(16) and (17). Thus, we can test the algorithm by comparing the statistics of the maps $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$ given by Q and U [eqs.(33) and (34)] with that directly calculated from E and B of eq.(32).

3.2. Recovery of spatial structures

The scalar functions ψ_E and ψ_B are taken to be sample A.) Gaussian function $\psi_{E,B}(x, y) = a_{E,B} \exp -(x^2 + y^2)/2d^2$; sample B.) the Legendre function $\psi_{E,B}(x, y) = a_{E,B} P_m(x) P_m(y)$. Both samples are in the area $-0.5 \leq x \leq 0.5$ and $-0.5 \leq y \leq 0.5$ and pixels 512×512 , i.e. $J = 8$. The coefficients a_E and a_B are used to adjust the ratio of the powers of $\mathbb{E}_{l,l'}$ and $\mathbb{B}_{l,l'}$. We use $a_E = 1$ and $a_B = 1/10$. That is, the power of E -mode is larger than B mode by a factor 10^2 . The maps of $\mathbb{E}_{l,l'}$ for samples A and B in the central square 32×32 pixels are shown Figure 1. The maps of $\mathbb{B}_{l,l'}$ have the same shape of Figure 1, but the intensity is weaker than Figure 1 by a factor 10.




Fig. 1.— The DWT maps of $\mathbb{E}_1$ of sample A: $\psi_E = \exp[-(x^2 + y^2)/2d^2]$, and $2d^2 = 1600$ (left), and sample B: $\psi_E = \psi_B/a_B = P_m(x)P_m(y)$, and $m = 100$ (right).

As mentioned in §3.1, with ψ_E and ψ_B one can produce the maps of Q and U by eqs.(33) and (34). Using noise-added maps of Q and U , we can further calculate noisy variables $\mathbb{E}_{l_1,l_2}$ and $\mathbb{B}_{l_1,l_2}$ with eqs.(16) and (17). This is the recovered maps of $\mathbb{E}_{l_1,l_2}$ and $\mathbb{B}_{l_1,l_2}$. Figures 2 and 3 present the recovered maps of $\mathbb{E}_{l_1,l_2}$ and $\mathbb{B}_{l_1,l_2}$ for samples A and B , respectively. The signal-to-noise ratios (S/N) are S/N=10, 50 and 100 from left to right. Comparing Figures 2 and 3 with Figure 1, we can conclude that the spatial structures of E mode maps can be well recovered with the noisy maps Q and U if $S/N \geq 10$. The recovery of B mode structures is relatively poor. For sample A (Fig. 2), we may pick up the original structures of B field




Fig. 2.— The maps $\mathbb{E}_{l_1, l_2}$ (up panels) and $\mathbb{B}_{l_1, l_2}$ (bottom panel) of sample A , which are recovered by eqs.(16) and (17) with noisy maps Q and U , and the signal-to-noise ratios are taken to be $S/N=10$ (left), 50 (middle) and 100 (right).

with all $S/N \geq 10$ noisy maps of Q and U , while for sample B , the structures of B field can not be seen with $S/N = 10$ map. That is, the structure identification of sample A is much better than sample B . This is because the field of sample A is highly inhomogeneous, while sample B is not so inhomogeneous. The latter is easily contaminated with a statistically homogeneous Gaussian field.

3.3. Recovery of power spectrum

We now turn to the recovery of the power spectrum. For wavelet Daubechies 6, the non-zero elements of the matrix $T_{l, l'}^n$ are in a band $|l - l'| \leq 4$, and therefore, cells distant from boundary, larger than $\Delta l = 4$, will be less affected by the boundary. Thus, one may expect that the power spectrum recovery would be reasonable with dropping 4 boundary cells.

Figures 4 and 5 show the DWT power spectra of $\mathbb{E}_{l, l'}$ and $\mathbb{B}_{l, l'}$ of both original and recovered samples of sets A and B , respectively. It includes 1.) the power spectra of the original maps, i.e. the map directly given by E and B [eq.(32)]; 2.) the ratio P_j^o/P_j^r , where P_j^o is the original power spectra from maps $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ of eq.(32), and P_j^r is the recovered




Fig. 3.— The same as Figure 3, but for sample B .

power spectra of maps Q and U with eqs.(16) and (17) without dropping boundary cells; 3.) the same as 2.) but dropping 4 boundary cells in the recovered power spectra.

In Figures 4 and 5, the scale $\mathbf{j} = (j_1, j_2)$ is described by an effective scale defined as j_{eff} as $(1/2^{j_{\text{eff}}}) = [(1/2^{j_1})^2 + (1/2^{j_2})^2]^{1/2}$. The samples are symmetric with respect to $x \rightleftharpoons y$. The power of mode (j_1, j_2) should be the same as (j_2, j_1) . Thus, for $J = 8$, the available pairs (j_2, j_1) are (4,4), (4,5), (4,6), (4,7), (5,5), (5,6), (5,7), (6,6), (6,7) and (7,7), corresponding to $j_{\text{eff}} = 3.50, 3.84, 3.95, 3.98, 4.50, 4.84, 4.96, 5.50, 5.84, 6.50$. The modes on scales with $j_1, j_2 \leq 3$ are dropped, as all cells are affected by the boundary effect.

We see from Figures 4 and 5 that the power spectra can indeed be well recovered by dropping 4 boundary cells. However, the boundary effect of sample A are less serious than sample B . This is because, for sample A , both $\psi_{E,B}(x, y)$ and $\partial_n \psi_{E,B}(x, y)$ are very small at boundary. The contribution to power by boundary cells is low. On the other hand, for sample B , the power spectra recovered without dropping boundary cells are significantly different from the original one. The B -mode power spectrum is hugely affected by the boundary. On small scale the derivative operator in the DWT representation is determined by data at a few discrete points, which leads to large error. This problem is always present in algorithms involving taking derivative on discrete data sets. Nevertheless the error caused by boundary is decreases rapidly as the scale increases.

To measure how good the recovery of power spectrum is, we use the ratio $P_{\mathbf{j}}^o/P_{\mathbf{j}}^r$ to




Fig. 4.— Left panel: The DWT power spectra P_j of the original maps $\mathbb{E}_1$ and $\mathbb{B}_1$ of sample A . The power spectrum on the top is for the E mode, and the lower is for the B mode. The ten data points correspond to $(j_1, j_2) = (4,4), (4,5), (4,6), (4,7), (5,5), (5,6), (5,7), (6,6), (6,7)$ and $(7,7)$ from left to right. The power ratio E/B is equal to 10^2 . Middle panel: the ratio P_j^o/P_j^r , where P_j^o is the original power spectra from maps $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ of eq.(32), and P_j^r is the recovered power spectra of Q and U with eqs.(16) and (17) and without dropping boundary cells. The top is for E mode, and bottom is for B mode. Right panel: the same as middle panel, but with 4 boundary cells dropped.

describe the deviation of the recovered power spectrum with noisy maps from the original one. All error bars are the variances calculated from 100 independent noisy maps. The results are plotted in Figures 6 and 7.

First we see that the effect of Gaussian noise is small at larger scales, because the noise is added on each pixels (finest scale) of the maps Q and U , and the uncertainty on large scales is suppressed. This point can also be seen from the fact that the error bars of modes $(4,7), (5,7), (6,7)$ and $(7,7)$ are much larger than others. It is because the Gaussian noise on smallest scales, j_1 or $j_2 = 7$, is not suppressed.

Figures 6 and 7 show that other than the modes with j_1 or $j_2 = 7$, the power of E mode can be reasonably recovered up to mode $(6,6)$, or $J_{\text{eff}} = 5.5$, when $S/N = 10$. As expected, the recovery for B mode generally is poor. Nevertheless, we can recover the DWT powers of B mode till $(5,5)$, or $J_{\text{eff}} = 4.5$, when $S/N=50$ (sample A) or $S/N=10$ (sample B).

An interesting point shown in Figures 6 and 7 is that the effects of noise on samples A and B are different. The error bars of sample A generally are larger than that of sample B . This is probably because for sample A , other than the central part, most cells are smooth, and have low local fluctuations. For those cells, the fluctuations of noise will strongly contaminate the power of original field, especially when derivative is involved. On the other hand, for




Fig. 5.— The same as Figure 4, but for sample B .

sample B , most cells have relatively stronger local fluctuations, and the effect of noise is relatively low.

4. Tests with samples of Gaussian random fields

4.1. Samples

With the preparation given in the previous section, we can consider the case that $\psi_E(x, y)$ and $\psi_B(x, y)$ as random fields. The sample of E and B can still be generated with the same procedure of §3.1, but $\psi_E(x, y)$ and $\psi_B(x, y)$ are taken to be Gaussian random fields with Fourier power spectra $a_E k^{-\alpha}$ and $a_B k^{-\alpha}$, respectively, and $\alpha = 3.6$. The variable $k^2 = k_x^2 + k_y^2$, and k_x, k_y are the Fourier variables of x, y space, respectively. The constant factors a_E and a_B are used to adjust the ratio of E/B power. From eq.(32), the power spectra of E and B are

$$P_E = a_E k^{2-\alpha}, \quad P_B = a_B k^{2-\alpha}. \quad (35)$$

We produce the maps in an area described by coordinate (x, y) in range $-0.5 \leq x \leq 0.5$ and $-0.5 \leq y \leq 0.5$ with pixelized into 512×512 . With maps E and B , one can find the maps $\mathbb{E}$ and $\mathbb{B}$ by eqs.(13), and (14).

The DWT power spectrum of $\mathbb{E}$ and $\mathbb{B}$ is shown in Figure 8. Since $J = 8$, the available modes (j_1, j_2) still are (4,4), (4,5), (4,6), (4,7), (5,5), (5,6), (5,7), (6,6), (6,7) and (7,7). The modes with $j_1, j_2 \leq 3$ are dropped, as they have only boundary cells. The ratio of the E/B power is taken to be 10. The error bars are from the variance of 100 samples. We see from Figure 8 that the powers of modes (4,7), (5,7) and (6,7) are nearly about the same as (7,7).




Fig. 6.— The ratio P_j^o/P_j^r for sample A , where P_j^o is the power spectrum of the original maps $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$, and P_j^r is calculated by eqs.(30) and (31) from Q and U with noise addition on the level of S/N equal to 10 (left), 50 (middle), and 100 (right). In each panel, the top is for E mode, and the bottom is for B mode.

Similarly, the powers (4,6), (5,6) are nearly about the same as (6,6); the power (4,5) is nearly about the same as (5,5). It is because in the case of $j_1 < j_2$, the power is dominated by the small scale j_2 .

4.2. Effects of random field

Unlike the maps in §3, all the maps of $\psi_E(x, y)$, $\psi_B(x, y)$; Q , U ; and $\mathbb{E}$, $\mathbb{B}$ are random fields. A serious problem caused by random fields is that the power of E mode may leak to B mode, and vice versa. That is, even when the original B mode power is zero, the recovered B mode power would not be zero.

To demonstrate the power leakage, we take $\psi_E(x, y)$ to be a Gaussian random field with the same Fourier power spectrum as Figure 8, while $\psi_B(x, y)$ to be 0. That is, the power of B mode originally is zero. Figure 9 presents the recovered DWT power spectra of E - and B -modes. We see that the recovered E -mode power spectrum is nearly the same as the original one shown in Figure 8, except that the recovered power spectrum on the finest scale is a little smaller than the original one. However, the recovered B -mode power spectrum is not zero. It is spurious B power. It arises from the leaking of E mode power to B mode. On large scales $j_{\text{eff}} \leq 4$, the ratio of the E/B power is about 10^4 , while on small scales $j_{\text{eff}} \geq 6$, this ratio is less than 10^2 . This is caused by the variance of random field. Thus, one may conclude that for the 512×512 sample of a Gaussian random fields of eq.(35), the developed algorithm would be effective only if the ratio E/B is less than 10^2 on small scales.




Fig. 7.— The same as figure 6, but for sample B .

As a comparison, we plot Figure 10, in which the $\psi_E(x, y)$ is given by samples A and B, while $\psi_B(x, y) = 0$, i.e. the power of B mode originally is also zero. Figure 10 shows that the recovered B -mode powers are also not zero. However, it generally is less than the original one by at least 3 orders. That powers seem to come from the numerical processes. Therefore, the errors caused by the variance of random fields are serious.

4.3. Recovery of E , B power spectra

As in §3.3, we measure the soundness of the recovery of power spectrum by the ratio P_j^r/P_j^o , where P_j^o is the power spectra of original maps $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$ from eq.(32), and P_j^r is the recovered power spectra from noisy maps of Q and U . The Gaussian noise added on the maps Q and U are on the levels $S/N=100$, 20 and 10. Similar to §3.3, four boundary cells are dropped. The results are plotted in Figures 11, 12 and 13, for which the ratio of the powers of E and B are equal to, 10, 20 and 100, respectively.

Figure 11 shows the powers of E mode can be recovered on all scales $j_{\text{eff}} \leq 6$ on all noise levels. On the smallest scale, $j_{\text{eff}} = 6.5$, the ratio P_j^r/P_j^o of E mode is slightly lower than 1. This deviation is almost independent of the level of S/N . Therefore, the errors mostly are not due to the Gaussian noise addition, but from the effect of leakage. This point is consistent with the leaking shown in Figure 9, which also give a little small power on the smallest scale. More interesting, Figure 11 shows that the B mode can be perfectly recovered on all scales and all noise levels considered.

Figure 12 presents the case of $E/B = 20$. The results on scales $j_{\text{eff}} \leq 5.5$ are about the same as the case of $E/B = 10$, while the deviations of P_j^r from P_j^o on scales $j_{\text{eff}} > 5.5$ are




Fig. 8.— The power spectra of $\mathbb{E}$ (higher one), $\mathbb{B}$ (lower one), for which ψ_E and ψ_B are Gaussian random field with the Fourier power spectra $a_E k^{-3.6}$ and $a_B k^{-3.6}$, respectively. The ten data points correspond to $(j_1, j_2) = (4,4), (4,5), (4,6), (4,7), (5,5), (5,6), (5,7), (6,6), (6,7)$ and $(7,7)$ from left to right. The error bars are from 100 samples of the Gaussian random field $\psi_E(x, y)$ and $\psi_B(x, y)$. The ratio of powers of E and B modes is equal to 10.

larger than that of $E/B = 10$. On small scales, the recovered E powers, P_j^r , are little lower than the original power P_j^o , while the recovered B powers are little higher than the original power.

Figure 13 is for the case of $E/B = 100$. It shows that the recovered E mode power spectrum is still good on scales $j_{\text{eff}} \leq 5.5$ for all S/N. However, on scales $j_{\text{eff}} > 5$, the recovered B mode power spectrum generally is higher than the original one. This deviation is expected, as Figure 9 shows that the leaked power from E mode to B mode can be as high as 1% on small scales. Nevertheless, the recovered B mode power spectrum is reasonable on scales $j_{\text{eff}} < 5$, even when the S/N is equal to 10. That is, one can pick up the weak signal of B mode with the DWT algorithm even when the Gaussian noise level of Q and U maps is comparable with the B mode signal.

5. Discussions

The relationships between the polarization maps of (E, B) and (Q, U) are differential. For pixelized samples of Q and U in finite area, the algorithm of E/B decomposition should be able to properly handle the derivative operation on a spatially discrete and noisy data




Fig. 9.— DWT power spectra of E mode (top) and B mode (bottom). The $\psi_E(x, y)$ is a Gaussian fields with the same Fourier power spectrum as Figure 8, while taking $\psi_B(x, y) = 0$.

set. The derivative operator ∂_x is a continuous linear operator to mapping functions defined in Hilbert space, while the functions Q and U are defined in space spanned by bases u_i , in which i is a set of finite index. Therefore, we should approximate the derivative operator from mapping between functions defined in Hilbert space, to a mapping in subspace spanned by n_i .

What we need to calculate is

$$Of = g, \quad (36)$$

where O is a linear continuous operator, like Laplace or derivative, and f and g are function of x, y in continuous space $0 < x, y < L$. However, we don't know f , but only the discretized $\tilde{f}$, which is given in N pixels (cells). That is, $\tilde{f}$ can be expressed as

$$\tilde{f}(x, y) = \sum_{k=1}^N \alpha_k w_k(x, y), \quad (37)$$

where function $w_i(x, y)$ is the binning function of pixel k , and α_k is the observed f at pixel k . The simplest binning function would be the top-hat window function of pixel k .

With N -dimensional space spanned by bases $[v_1(x, y), \dots, v_N(x, y)]$, eqs.(36) and (37) yield

$$g_i \equiv \langle g, v_i \rangle = \sum_{k=1}^N \langle Ow_k, v_i \rangle \alpha_k. \quad (38)$$




Fig. 10.— DWT power spectra of E mode (top) and B mode (bottom). The $\psi_E(x, y)$ is given by sample A and sample B, while taking $\psi_B(x, y) = 0$. The left panel is for sample A, while the right panel is for sample B.

The matrix $O_{ik} \equiv \langle Ow_k, v_i \rangle$ gives a discretization of operator O from the space $0 < x, y < L$ to a finite-dimensional subspace $[v_i]$.

A Galerkin discretization requires the following equation to be hold for all v_i

$$\langle (g - Of), v_i \rangle = 0 \quad (39)$$

That is, eq.(36) should be hold in the subspace spanned by bases $[v_1(x, y), \dots, v_N(x, y)]$. In this case, the matrix O_{ik} is a linear operator to map functions defined in the subspace v_i . If f is a function of the subspace v_i , $g = Of$ is also a function of the subspace.

It can be seen from eqs.(36) - (38) that the discretization of operator O actually is inevitable for all algorithms. To treat the data eq.(37), we must use some base v_i in the spatial domain. It will yield a matrix O_{ik} , regardless whether eq.(39) is hold with the bases v_i . The Galerkin method gives a best discretization of eq.(36) or the operator O (e.g. Louis et al. 1997).

We use $\phi_{J,l}(x)\phi_{J,l'}(y)$, $l, l' = 0 \dots 2^J - 1$ to be the bases to span the subspace with dimension $N = 2^J \times 2^J$. It can be shown that the conditions of Galerkin discretization, eq.(39), will be satisfied for operator $O = \partial_x, \partial_y, \partial_x^2$ and ∂_y^2 . That is, for any function $f(x, y)$ of the subspace spanned by bases $\phi_{J,l}(x)\phi_{J,l'}(y)$, $l, l' = 0 \dots 2^J - 1$, the result of Of are also functions of the subspace. This is the wavelet-Galerkin discretization. Matrix $\langle Ow_k, v_i \rangle$ will be invertible. In this sense, the discretization does not lose information, or introduces false




Fig. 11.— The ratio P_j^r / P_j^o for Gaussian random field $\psi_{E,B}(x, y)$ with Fourier power spectra $a_{E,B} k^{-3.6}$. The top panels are for E mode, and bottom for B mode. The ratio of the powers E/B is equal to 10. The maps Q and U are added noises with the level of S/N equal to 100 (left), 20 (middle) and 10 (right).

data or correlations.

Obviously, the Galerkin discretization is not unique. One can use different wavelets to do the Galerkin discretization. To apply the discretization, the matrix $O_{ik} \equiv \langle Ow_k, v_i \rangle$ should have the following desirable properties. First, the matrix O_{ik} has to be sparse, narrowly banded. In this case, one can effectively minimize the information lose due to dropping boundary modes. A narrowly banded matrix can also effectively reduce the spreading of errors among cells with different $\mathbf{l}$. Secondly, in order that the errors not increase with the size of the matrix N (number of data), the “width” of the band in which the matrix elements O_{ik} is non-zero, should be independent on N .

6. Conclusions

The algorithm developed in this paper can be summarized as follows

- From observed noisy and discrete maps $Q(x, y)$ and $U(x, y)$ we calculate their DWT maps Q_{l_1, l_2} and U_{l_1, l_2} on the finest scale $\mathbf{j} = (J, J)$, which is given by the resolution.
- Using eqs.(16) and (17) we decompose Q_{l_1, l_2} and U_{l_1, l_2} into $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$.
- Using eqs.(19) and (20) we calculate WFCs $\tilde{\epsilon}_{\mathbf{j}, 1}^E$ and $\tilde{\epsilon}_{\mathbf{j}, 1}^B$ on scales (j_1, j_2) and $j_1, j_2 \leq J$.
- Using the WFC maps $\tilde{\epsilon}_{\mathbf{j}, 1}^E$ and $\tilde{\epsilon}_{\mathbf{j}, 1}^B$ we calculate the DWT power spectra by eqs.(30) and




Fig. 12.— The same as Figure 11, but the power ratio of E and B modes is equal to 20.

(31).

- We identify spatial structures with maps of $\mathbb{E}_{l_1, l_2}$ and $\mathbb{B}_{l_1, l_2}$.

With this algorithm, it is possible to recover the power spectrum of B -mode random fields from noisy Stokes parameter maps Q and U when the power ratio E/B is as high as 10^2 , and the S/N is equal to or higher than 10. For samples with given structures, the B -mode structure can also be identified when the power ratio E/B is equal to 10^2 . Besides power spectrum, the DWT variables of SFCs ($\epsilon_{j,1}^E$, $\epsilon_{j,1}^B$) and WFCs ($\tilde{\epsilon}_{j,1}^E$, $\tilde{\epsilon}_{j,1}^B$) can be used for high order statistics, such as high order moments, scale-scale correlation, cross correlation between the E and B and other maps.

With the DWTs, one can construct orthogonal, divergence-free vector wavelets. It has been used for a local analysis of the velocity field of incompressible turbulence (Urban 1995; Kishida et al. 1999; Albukrek et al. 2002). The divergence-free B field is similar to a 2-D velocity field of turbulence of incompressible fluid (e.g. Pina 1998). Therefore, it would be valuable to further study the DWT E/B decomposition with the divergence-free vector wavelets.

We thank Dr. Priya Jamkhedkar for her helps. Liang Cao acknowledge the support by the Knowledge Innovation Program of the Chinese Academy of Sciences(0990611009) and the CAS Special Grant for Postgraduate Research, Innovation and Practice(0992921009). This work is partially supported by NSFC(10533030, 10878001), US NSF AST-0507340, and ICRAnet grant 2008.




Fig. 13.— The same as Figure 11, but the power ratio of E and B modes is equal to 100.

A. Derivative operator in wavelet representation

In the DWT space, the operators of derivatives are represented as a matrix

$$T_{j;l,l'}^{(n)} \delta_{j,j'} = \int \phi_{j,l}(x) \partial_x^n \phi_{j',l'}(x) dx. \quad (\text{A1})$$

That is, the matrix is diagonal with respect to j, j' . $T_{j;l,l'}^{(n)}$ is given by (Beylkin 1992; Kwon 1998)

$$T_{j;l,l'}^{(n)} = \frac{1}{h^n} r_{l-l'}^{(n)} \quad (\text{A2})$$

where $h = 1/2^j$. The matrix elements $r_{l-l'}^{(n)}$ depend on the type of wavelet. For Daubechies 6 wavelet, the non-zero coefficients $r_{l-l'}^{(n)}$ are $|l - l'| \leq 4$. The values of $r_{l-l'}^{(n)}$ are listed in Table 1, in which $m = l - l'$. Therefore the coefficients of $T_m^{(n)}$ of eqs.(11) and (12) are given by

$$T_m^{(n)} = \frac{1}{h^n} r_m^{(n)}. \quad (\text{A3})$$

It is interesting to see that the non-zero band of first and second order derivative operators ∂_x and ∂_x^2 are the same. This is different from the estimation of derivative operator by differential approximation.

Table 1 Coefficient of $r_m^{(n)}$		
$l - l' = m$	$n = 1$	$n = 2$
4	1/2920	3/560
3	16/1095	4/35
2	-53/365	-92/105
1	272/365	356/105
0	0	-295/56
-1	-272/365	356/105
-2	53/365	-92/105
-3	-16/1095	4/35
-4	-1/2920	3/560

REFERENCES

- Albukrek,C.M., Urban, K., Rempfer, D. & Lumley, J.L. 2002, J. of Scientific Computing, 17, 49
- Bunn, E.F., Zaldarriaga, M. Tegmark, M., Oliveira-Costa, A. 2003, PRD, 67, 023501
- Beylkin, G. SIAM Journal on Numerical Analysis, 29, 1716, (1992)
- Cao, L., Chu, Y.Q., Fang, L.Z. 2006, MNRAS, 369, 645
- Cao, L., Liu, J.R., Fang, L.Z. 2007, ApJ, 661,641
- Chiueh, T. & Ma, C.J. 2002, ApJ, 578, 12
- Fang, L.Z. & Feng L.L. 2000, ApJ, 539, 5
- Fang, L.Z. & Thews, R. 1998, Wavelet in Physics(World Scientific)
- He, P., Feng,L.L. and Fang, L.Z. 2005, ApJ, 628, 14
- Kamionkowski,M., Kosowsky, A., Stebbins, A. 1997, Phys.Rev. D, 55, 7368
- Kishida, K., Araki, K., Kishiba, S, & Suzuki, K. 1999, Phys. Rev. Lett. 83, 5487
- Kwon, S.G. 1998, Bull. Korean Math. Soc. 35, 629
- Lewis, A. 2003, PRD, 68, 083509
- Lewis, A., Challinor, A. & Turok, N. 2002, PRD, 65, 3505

- Louis, A.K., Maass, P. & Rieder, A. Wavelets: Theory and Applications 1997, (John Wiley & Sons, New York)
- Mukherjee, P., Hobson, M. P., Lasenby, A. N. 2000, MNRAS, 318, 1157
- Pando, J., & Fang, L.Z. 1998, A&A, 340, 335
- Pando, J., Valls-Gabaud, D. & Fang, L.Z. 1998, Phys.Rev. Lett., 81, 4568
- Pericival, D. B., & Walden, A. T. 1993, Spectral Analysis for Physical Applications (Cambridge Uni. Press)
- Pina, E. 1998, J. Plasma Physics, 59, 719
- Sanz, J. L., Argeso, F., Cayn, L., Martnez-Gonzlez, E.; Barreiro, R. B., Toffolatti, L. 1999, MNRAS, 309, 672
- Seljak, U. 1997, ApJ, 482, 6
- Smith, K. M. 2006, PRD, 74, 0803002
- Smith, K. M. & Zaldrariaga, M. 2007, PRD, 76, 043001
- Urban, K. 1995, Adv. in Comp. Math. 4, 51
- Zaldrariaga, M., Seljak, U. 1997, Phys.Rev. D, 55, 1830